

ADVANCE

T5 & T8

PREHEAT TRIGGER START

Straight Lamps



NORMAL POWER FACTOR SOUND RATED A

Lamp Data		Circuit Volts	Min. Starting Temp. (F)	Catalog Number	Certifications					Line Current (Amps)	Input Power ANSI (Watts)	Ballast Factor	THD %	Dim.
Number	Watts				UL	CSA	E	RoHS	REACH					

F4T5 4W / F6T5 6W / F8T5 8W

1	8	120	50	LQ-106F-TP	✓				0.34	14	0.90	<20	R-4
		277		VLO-106F-TP	✓				0.17	13	0.90	<20	
2	8	120	50	LO-206-F-TP	✓				0.40	21	0.90	<20	R-4

F15T8

1	15	120	50	RLQ-120-TP♦	✓	✓			0.58	21	0.70	<30	R-4
				HM-1P20-TP▲	✓	✓			0.27	32	0.75	<20	T-2
		277		VHM-1P20-TP▲	✓	✓			0.12	32	0.78	<20	T-2
2	15	120	50	RL-2SP20-TP	✓	✓			0.55	50	0.72	<30	T-1
				HM-2SP20-TP▲	✓	✓			0.47	53	0.85	<15	T-2
		277		VM-2SP20-TP▲	✓				0.20	56	0.86	<20	T-2
		347		GM-2S20-TP▲	✓	✓			0.17	44	0.87	<25	T-2
3	15	120	50	RL-3SP20-TP	✓	✓			0.80	52	0.72	<30	R-5

F30T8

2	30	120	0	RC-2SP830-TP▲†●	✓	✓			0.70	82	0.93	<20	R-5
---	----	-----	---	-----------------	---	---	--	--	------	----	------	-----	-----

♦ Requires Circuit-Interrupting Lamp Holders ▲ High Power Factor † Class A Insulation ● Sound Rated B