

# RS2232TP

The Advance RS-22-32-TP-W magnetic ballast operates two (2) FC8T9 lamps at 120V.

This ballast is great for areas that require normal lighting! rapid start ballast is typically used in offices, board rooms, and retail.

Also operates FC12T9, and Fluorescent lamps.

## SPECIFICATIONS

- Type: Magnetic Circular Fluorescent
- Start Method: Rapid Start
- Lamps: two FC8T9
- Input Voltage: 120V

## FEATURES

- Minimum Temperature: 50°F - 10°C
- Sound Rated Class A
- 96% power factor
- 5 years warranty

## DIMENSIONS

- Length: 6.5"
- Height: 1.5"
- Width: 2.3"
- Mounting Height: 6"

Lamp Type	Num. of Lamps	Rated Lamp Watts	Min. Start Temp (*F/C)	Input Current (Amps)	Input Power (Watts)	Ballast Factor	MAX THD %	Power Factor	Lamp Current Crest Factor	B.E.F .
* (1)FC8T9 & (1)FC12T9	2	2232	50/10	0.40	46	0.70	15	0.96	1.7	1.52