

IMAGE COMING SOON

Product Number: 75727

Order Abbreviation: M1000MULTISKIT

General Description: 120/208/240/277/480V 5-tap magnetic core and coil M47 ballast for 1000W Metal Halide lamp

Product Information

| | |
|-----------------------------------|---------------------------|
| Abbrev. With Packaging Info. | M1000MULTISKIT 1/CS 1/SKU |
| ANSI Code | M47 |
| Capacitor Diameter | 55 |
| Capacitor Height | 90 |
| Capacitor MFD & VAC | 24 ?F 540 VAC |
| Circuit Type | CWA |
| Family Brand Name | METALARC |
| Nominal Voltage (V) | 120/208/240/277/480 |
| Open Circuit Voltage (V) | 410 |
| Power Factor | >0.9 |
| Primary Lamp Type | M1000 |
| Starting Method | OCV |
| Starting Temperature - Fahrenheit | -30°C |
| Starting Temperature - Celsius | -22°F |
| Wiring Method | LEADS |
| Product Weight (g) | 10900.00 |
| Supply Frequency (Hz) | 60 |

Footnotes

- Product is a kit containing the core & coil, capacitor, ingitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Product contains installation instructions