



## TT5 COMPACT FLUORESCENT

### TT5 INSTANT START, <20%THD

Operates FT40DL

Primary Lamp Type	No of Lamps	Input Voltage (VAC)	Product Number	Ordering Abbreviation	Pkg Qty	Ballast Factor	Input Wattage (W)	Input Current (Amps)	Wiring Method	Symbols & Footnotes
FT40DL	1	120	49641	QT1X40/120DL	10	0.96	40	0.33	Leads	Ⓢ Ⓣ 1,2,4,5,6,7,8,9,10,11,12,13
		277	49642	QT1X40/277DL				0.14		
	2	120	49643	QT2X40/120DL	10	0.96	75	0.63	Leads	Ⓢ Ⓣ 1,2,4,5,6,7,8,9,10,11,12,13
			277	49644						
	3	120	49645	QT3X40/120DL	10	0.96	110	0.94	Leads	Ⓢ Ⓣ 1,2,4,5,6,7,8,9,10,11,12,13
			277	49646						

### TT5 PROGRAMMED START, <10%THD

Normal Light Output

Primary Lamp Type	No of Lamps	Input Voltage (VAC)	Product Number	Ordering Abbreviation	Pkg Qty	Ballast Factor	Input Wattage (W)	Input Current (Amps)	Wiring Method	Symbols & Footnotes
FT40DL	1	120	50320	QTP1X40TT5/120PSN F	20	0.88	38	0.32	Leads	Ⓢ Ⓣ ④ 2,4,6,8,9,10,11,12,13,16
			50330	QTP1X40TT5/277PSN F						
	2	120	50340	QTP2X40TT5/120PSN F	20	0.88	76	0.63	Leads	Ⓢ Ⓣ ④ 2,4,6,8,9,10,11,12,13,16
			50350	QTP2X40TT5/277PSN F						
	3	120	50360	QTP3X40TT5/120PSN B	20	0.88	110	0.92	Leads	Ⓢ Ⓣ ④ 2,4,6,8,9,10,11,12,13,16
			50370	QTP3X40TT5/277PSN B						

## T4 COMPACT FLUORESCENT

### PROGRAMMED START UNIVERSAL VOLTAGE <10% THD

Product Number	Ordering Abbreviation	Pkg Qty	Primary Lamp Type	No. of Lamps	Ballast Factor	Input Voltage (VAC)	Input Wattage (W)	Circuit Type	Wiring Method	Symbols & Footnotes	
51718	QTP 1/2X13CF/UNV BS	20	13W DD/E, T/E	1	1.0	Universal 120-277	16	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 8,9,10,11,17,25,28	
51778	QTP 1/2X13CF/UNV QS	16		2	1.0		29				
51748	QTP 1/2X13CF/UNV TS	20		2	1.0		29				
51723	QTP 1/2X18CF/UNV BS	20	18W DD/E, T/E	1	1.0	Universal 120-277	20	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 8,9,10,11,17,25,28	
51783	QTP 1/2X18CF/UNV QS	16		2	1.0		38				
51753	QTP 1/2X18CF/UNV TS	20		2	1.0		38				
51733	QTP 2X26CF/UNV BS	20	26W DD/E, T/E	1	1.0	Universal 120-277	28	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 8,9,10,11,17,25,28	
51793	QTP 2X26CF/UNV QS	16		2	1.0		54				
51763	QTP 2X26CF/UNV TS	20		32W DT/E	1		0.98				35
				42W DT/E	1		1.0				45
Note: QTPx26CF/UNV models now also operate one lamp as shown above											
51738	QTP 1/2XCF/UNV BM	20	26W DD/E, T/E	1	1.02	Universal 120-277	28	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 6,8,9,10,11,17,25,28	
51798	QTP 1/2XCF/UNV PM	18		2	1.02		57				
51768	QTP 1/2XCF/UNV TM	18		32W DT/E	1		0.97				36
				42W DT/E	1		1.0				46
51743	QTP 2X26/32/42CF/UNV BM	20	26W DT/E	2	1.02	Universal 120-277	54	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 6,8,9,10,11,17,25,28	
51803	QTP 2X26/32/42CF/UNV PM	18		2	0.96		69				
51773	QTP 2X26/32/42CF/UNV TM	18		2	0.95		94				
51740	QT 1X57CF/UNV BM	20	57W DT/E	1	1	Universal 120-277	62	Series	Wiretrap Connectors	Ⓢ Ⓣ ④ 6,8,9,10,11,17,25,28	
51800	QT 1X57CF/UNV PM	18		1	0.92		71				

• Data shown is based on primary lamp type.