

Universal Basic-12 B340R120HP T12 Electronic Fluorescent Ballast



Universal Basic-12 B340R120HP T12 Electronic Fluorescent Ballast

Universal Basic-12 B340R120HP T12
Electronic Fluorescent Ballast



- [Product Description](#)
- [Accessories](#)
- [Product Video](#)
- [Reviews](#)

Details



Universal Magnetek Electronic Fluorescent T12 Ballast

- Active Power Factor Correction.
- Basic-12® ballasts provide electronic energy saving performance, generating energy savings of greater than 20% when replacing a magnetic ballasts while still using the same T12 lamps.
- High Frequency Operation
- Remote Mounting: 12 ft. max. lead length, 18 AWG
- High frequency electronic ballast for 3 F40T12 lamps (and others as indicated below)

Additional Information

Order Code	B340R120HP
Input Volts	120V
Brand	Universal Basic-12
Family	N/A
Mfg #	B340R120HP
# of Lamps	2 Lamps, 3 Lamps
Product Data Sheet	B340R120HPBasic-12
Certifications	CSA, UL
Equivalents	NA
Start Method	Rapid Start
Starting Temperature	50°F, 10°C
Lamps	(3) F30T12, (3) F30T12ES, (2/3) F40T12, (3) F40T12ES, (3) F40T10, (3) FT39W/2G11
Dimensions	9.50" x 2.40" x 1.55"
Case Size	10
Warranty	36 Month Universal Limited Warranty
UPC	768386061700