

# CLASS 2 PLUG-IN ELECTRONIC 12V

## Transformers

# WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

### PRODUCT DESCRIPTION

Low Voltage plug-in Class II electronic transformer designed to be used as portable or plug-and-play style transformer. Contains an on/off toggle switch at the base and a 6' detachable cord.

### FEATURES

- 1W minimum load
- UL listed Class 2 plug-in electronic transformers
- Plug-in power supply with on/off switch and 6' detachable cord
- Class 2 transformers are required for most cabinet listed fixtures

### SPECIFICATIONS

**Construction:** Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

**Output:** 12V

**Frequency:** 20khz

**Dimming:** Dimmable. Consult factory for options.

**Details:** Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits.

**Standards:** UL Listed

### ORDER NUMBER

Model	Finish	Output	L	W	H
<b>EN-1260-P-AR</b>	<b>BK</b> Black <b>WT</b> White	12V, 1 x 60W	2¾"	1⅝"	1¾"

### ACCESSORIES

#### Multiple Terminal Block

Accommodates up to 6 output connections for 14 AWG wires. Terminal block is used to easily wire together multiple output connections for a neat under cabinet installation without the use of open splices. Perfect for wiring up to 3 button lights at 20W or 6 button lights at 10W.

Model	L	W	H
<b>MTB-01</b>	3¼"	1¾"	⅞"

**EN-1260-P-AR-\_\_\_\_\_**

Example: **EN-1260-P-AR-BK**

wacighting.com  
Phone (800) 526.2588  
Fax (800) 526.2585

Headquarters/Eastern Distribution Center  
44 Harbor Park Drive  
Port Washington, NY 11050

Central Distribution Center  
1600 Distribution Ct  
Lithia Springs, GA 30122

Western Distribution Center  
1750 Archibald Avenue  
Ontario, CA 91760